

Zatwierdzona lista baterii

Wersja: Growatt-LV48-0007

Data wydania: 19.01.2025

Wydane przez: ShenZhen Growatt New Energy Co., Ltd.

Deklaracja zgodności:

Growatt oświadcza, że następujące modele inwerterów są kompatybilne z poniższymi markami akumulatorów.

Osoba odpowiedzialna: Daisy Xiao

Modele inwerterów:

- SPH/SPM: SPM 3-6kTL-HU, SPM 8-10kTL-HU, SPH 8-10kTL-HU-US(B), SPH 10000TL-HU, SPH 10000TL-HU-US
- SPE: SPE 8000-12000 ES, SPE 3.5-6KTL HVM-G2, SPE 6000-12000 US
- SPF: SPF 6000ES Plus, SPF 3-5k ES, SPF 3.5-5k ES Lite, SPF 2-5kTL HVM, SPF 3000TL LVM, SPF 3.5-5kTL HVM-Pro, SPF 4-12kT HVM, SPF 4-12kT DVM, SPF 4-18kT DVM-MPV
- WIT: WIT 4-15k-HU

Lista baterii:

Bateria		Inwerter		
Marka baterii	Model baterii	Model Inwertera	Komunikacja RS485 / CAN	Ustawienie inwertera
Growatt	Hope 5.5L-A1,Hope 5.0L-B1	SPH/SPM HU	RS485	00
		SPE, SPF		L01
	ALP 5.0L-E2-US, ALP 5.0L-E1, AXE 5.0L - C1 Hope 5.5L-A1,Hope 5.0L-B1, Hope 14.3L-A1	SPH/SPM HU	CAN	01
		SPE, SPF		L51
		WIT		√
Sacolar	STR5.5-A1	SPH/SPM HU	CAN	01
		SPE, SPF		L51
		WIT		√
		SPH/SPM HU	RS485	00
		SPE, SPF		L01
Energys	OGHB1548-Li	SPH/SPMHU	CAN	02
Topband	TB48100F-T110AD	SPH/SPM HU	RS485	03
		SPE, SPF		L01
PYLON	US2000B,US3000,US2000C,US3000C,Pelio-L UP5000, US5000, Force L1, Force L2, UF5000	SPH/SPMHU	CAN	04
		SPE, SPF		L52
Dyness	DL2.5, DL3.6, DL5.0, DL5.0C, DL5.0e, DL5.0X; PowerboxG2,PowerBrick,PowerboxPro,PowerDepotH5B; B4850, B3, A48100, B51100, BX51100	SPH/SPM HU	CAN	01
		SPE, SPF		L51
		WIT		√
		SPH/SPM HU	RS485	00
		SPE, SPF		L01
PYTES	V5°,E-BOX-48100R	SPH/SPM HU	CAN	01
		SPE, SPF		L51
		WIT		√
		SPH/SPM HU	RS485	00
		SPE, SPF		L01

Raystech	RT5427, RT10854, RT5000 LM, RT5000 B, RT5427-LV-RACK, RT5120M	SPH/SPM HU	CAN	01
		SPE, SPF		L51
		WIT		√
EG4	EG4-LL, SR-48-100-LP4-IN-02, WM-48-100-IN-00, WP-16/280-1AWLL, WM-48 280-LL-00, WM-48-280-1-IN-LL-00	SPH/SPM HU	CAN	01
		SPE, SPF		L51
		WIT		√
Zetara	ZLES5000R, ZRLVESS5KR, ZRLVESS10KR, ZRLVESS5KR-LP, ZRLVESS5KR-V3, ZLES5000W, ZRLVESS5KW-SC, ZRLVESS10KW, ZRLVESS14.3KW, ZRLVESS14.3KW-OD, ZRLVESS5KHS, ZRLVESS5KVS	SPH/SPM HU	CAN	01
		SPE, SPF		L51
		WIT		√
Soluna	Soluna EOS 5K Pack Soluna EVO 5K Pack Soluna 10K Pack LV Soluna Franz 9.6K Pack LV	SPH/SPM HU	CAN	01
		SPE, SPF		L51
		WIT		√
CF Energy	CFE-5100,CFE-5100S, CFE-2400,CFE-10H, CFE-5,CFE-WL10, CFE-WL15	SPH/SPM HU	CAN	01
		SPE, SPF		L51
		WIT		√
Briggs & Stratton	SPHI-6.6-L0 SPHI-13.2-L0 SPHI-19.8-L0 SPHI-6.6-L0-C SPHI-13.2-L0-C SPHI-19.8-L0-C	SPH/SPM HU	CAN	04
		SPE, SPF		L52

Partnerzy Growatt Battery obsługujący komunikację zamkniętą

Shenzhen Growatt New Energy Co.,Ltd

Add 4-13/F,Building A,Sino-German(Europe)Industrial Park, Hangcheng Ave,Bao'an District,Shenzhen, China
Tel 0755 2951 5888 Web www.ginverter.com
Fax 0755 2747 2131 Email info@ginverter.com

Uwagi:

1. Należy ustawić tryb baterii na „Litowy” i wybrać odpowiedni tryb zgodnie z tabelą powyżej.
2. Klient powinien potwierdzić zgodność baterii z inwerterem Growatt u dostawcy.
Growatt nie ponosi odpowiedzialności za błędy komunikacyjne.
3. W celu zgłoszenia nowej baterii do listy kompatybilnych, należy kontaktować się mailowo:
 - Iverson Li: iverson.li@growatt.com
 - Daisy Xiao: zhenqi.xiao@growatt.com